

**Power Sequencer
SP-PC1008**



Features:

- Support 8 devices on-line at the same time.
- Multipurpose socket, accord with European and American standards.
- Configure a USB lighting interface.
- Rocker type switch.
- Each channel can be controlled independently.

Specification:

Technical Parameter	
Model	SP-PC1008
Maximum input current	80A
Single maximum output current	30A
Working voltage	220V-240V/50-60Hz
Each channel power	Up to 4500w
Input and output voltages	AC Input Voltages = AC Output Voltages
Output power socket	Multipurpose socket, accord with European and American standards.8 controlled multipurpose sockets on the back panel
Socket material	Each socket is made of phosphorus copper, which is installed only after inspection
Interval time of each switch	One second, each road with a switch indicator and a safety switch button(bypass) at the back
Electric relay	Ningbo Songle Brand(Original authentic product)
Circuit board	Using 60% high purity tin, high-end shunt technology, strengthened roughening treatment
Transformer	A&C (Original authentic product)
Power wire	3*6 square power wire, wire material configuration length 1.5 m

Voltage display	Diode, digital display voltmeter
Chassis height	1.5u(Compliance with cabinet according to standard)
Switch	Rocker type switch
Lighting configuration	Configure a USB lighting interface
Online support	Yes, support 8 devices on-line at the same time. On-line port: 6.5 socket
Controlled function	Yes, each channel can be controlled independently.
Filter	Capacitor filter