

# Economic Stereo Digital AM/FM Tuner with Mp3/USB SP-8TU



## Description:

The SP-8TU is an AM/FM stereo digital tuner with USB that provides advanced technology and convenient use for a public address background music source.

It is built-in AM/FM digital stereo tuner, it also integrate Mp3 player with USB on front panel, the USB input with priority over tuner. With stereo RCA output, one selector to pre-set the output between mono or stereo. Simple and easy use audio sources player for commercial audio system and PA sound system.

## Feature:

- Rack mount 19" 1U Economic digital stereo AM/FM tuner
- Industrial design for audio project, long term & stable use for public address system & BGM
- Built-in professional high-fidelity stereo digital radio system
- Station memory stores up to 60 channels.
- IR wireless remote control for all functions.
- Various high sensitivity tuning system: Manually, Automatic or Frequency direct input
- Previous and next station selection
- USB input on front panel
- Mono audio output
- RCA audio output jacks

## Specification:

Model	SP-8TU
Description	Stereo AM/FM Tuner with Mp3/USB
Antenna Input	75ohms
Audio Output	<500mV, 10Kohms( $\Omega$ ), un-balanced
Frequency Range	AM: 522KHz ~ 1620KHz, FM: 87MHz ~ 108MHz
S/N Ratio	AM:> 40dB, FM:> 45dB
THD	<0.01% at 1KHz
Frequency Response	20Hz ~ 18KHz
Power Cord	(3 x 0.5mm <sup>2</sup> ) x 1.5M (standard)
Power Supply	AC 220V $\pm$ 10%, 50-60Hz
Power Consumption	10 ~ 15W
Material	High-end aluminum panel, 19" 1U, brushed black Case: steel plate, black, elegant appearance
Net Weight/Dimension	2.30KG / 51 x 483 x 255mm
Gross Weight/Package	3.30KG / 530*380*120mm, 1pcs/ctn

## Rear Panel:

