

Bluetooth Hi-Fi Digital Stereo Mixer Amplifier SP-HA240B



Description:

The commercial and professional digital stereo mixer amplifier SP-HA240B integrates pre amplifier and power amplifier with rated 2*40W @8Ω speaker output.

The SP-HA240B is tabletop mini compact size design enjoys various media sources: Bluetooth, Mp3, USB, TF, FM, Aux in, MIC, Line input, REC audio output and headphone audio output.

It has elegant appearance and high reliable performance. Ideal for Hi-Fi home theater, SPA, retail stores, coffee shops, small restaurants classrooms and so on where there is background music system

Feature:

- Hi-Fi Digital Stereo Mixer Amplifier with Bluetooth/Mp3/USB/TF/FM/AUX IN/MIC/RCA.
- Digital class-D stereo power amplifier high efficiency design up to 85%.
- Desktop Hi-Fi amplifier with low distortion & acoustically accurate reproduction of music.
- This multipurpose digital Hi-Fi audio amplifier with LCD control display.
- Stereo output RMS 40 watts by two channels @8Ω, speaker output 4-16ohm.
- With Mp3/USB/TF/FM/Bluetooth audio sources and remote control.
- Microphone input & RCA line in & 3.5mm AUX in
- Headphone/audio output & Record audio output.
- MIC Priority swith to two modes: pager or mixing.
- Mic Echo & Master volume controls, bass and treble tone controls.
- LED indicators for overload protection, L & R cahnnels, power.

Specification:

Model	SP-HA240B
Description	Digital Stereo Mixer Amplifier with Multimedia
RMS Power Output	2*40W @8Ω
Speaker Output	4-16 Ohms
Built-in Sources	Bluetooth/Mp3/USB/TF/FM/AUX IN/MIC/RCA
Input	Microphone input & RCA line in & 3.5mm AUX in
Output	Headphone/audio output & Record audio output
Sensitivity	AUX/USB: 360mV, AUX/REC Line out: 420mV
Frequency Response	20Hz-22KHz
THD	<0.5%
S/N	70dB
Tone Control	Treble ±10dB, Bass ±10dB
Dimension/Net Weight	260*235*80mm/1.8KG

