Intelligent 16 Channel Audio Matrix Controller SP-16AMC





Feature:


- · Public address system classic cost-effective medium to big-scale sound system intelligent controller.
- · Ideal PA sound system controller for school, shopping mall, hotel, and intelligent office etc.
- · All in one intelligent PA sound system include 16 channel audio matrix, Mp3 player & USB, 16 zone remote paging system, fire alarm & voice evacuation system interface, weekly scheduled timer and power sequencer.
- · 16 Channel audio matrix controller with 16 channel inputs and 16 outputs.
- · Zone capacity expandable to 128 zones by cascaded 8 unit together, master controller and 7 units slave controllers.
- · All in one intelligent PA System controller built in 16 channel audio matrix, weekly timer, 16 zone speaker selector, Mp3 player, remote 16 zone paging controller, fire alarm and voice evacuation system interface and programmable power sequencer.

Specification:


Model	SP-16AMC
Description	Intelligent 16 Channel Audio Matrix Controller
Channel	16 channel inputs and 16 channel outputs
Max Capacity	128 zones by cascaded 8 units together
Call Station Input	Call station input 1-5, RJ45 port, 10kΩ, 10V, balanced
Input	Line 1-16: $10k\Omega$, 330mV, unbalanced RCA input EMC1: $10k\Omega$, 330mV, unbalanced
Output	Line 1-16: $10k\Omega$, 330mV, unbalanced RCA output EMC1: $10k\Omega$, 0.775mV, 0dB, unbalanced
Alarm	Alarm input: 0V, closed circuit contact Alarm output, 0V, closed circuit contact
Frequency Response	128×64 LCD display in English
Control	16 zone output volume controls; Menu buttons: up, enter & down ID dip switch; Master or slave dip switch
Protection	AC fuse 0.5A, 1PCS
Power Consumption	20W
Power Supply	AC 220-240V or 110-115V, 50~60Hz
Net Weight	7.2 KG
Product Dimension	483(W)*390(D)*133(H)mm
Gross Weight	8.8 KG/pcs
Package Size	520(W)x455(D)x185(H) mm, 1pcs/ctn







Connection Diagrams:



Fire Alarm Panel with Recorder